



GORILLA PRO

WIRELESS GAMING HEADSET



USER MANUAL



1. POWER BUTTON:

- press and hold for 3 seconds: turn on/off
- single click: Play/pause music
- double-click: switch to the next song
- three strokes: wake up the voice assistant (BT mode is valid)
- When the BT mode: single click to answer the incoming call, click again Hang up, hold for 2 seconds to reject the incoming call
- Power off status: press and hold the power button for 10 seconds to clear the pairing record

2. MICROPHONE MUTE/UNMUTE & MODE BUTTON

- on/off the microphone (Default is microphone on)
- double click to switch the previous song
- triple click to adjust between game mode and music mode
- long press 3 seconds to adjust between 2.4G mode and BT mode

3. VOLUME BUTTON

- turn up to increase the volume, turn down to reduce the volume

4. STATUS INDICATOR

- BT mode with blue LED, 2.4G mode with white LED,
- when battery is in charging, it's red LED, fully charged, blue LED on

5. CHARGING PORT / AUDIO INPUT PORT:

- plug in the charging cable to charge, support working while charging

Remarks:

To support headset is working while charging feature, users must plug USB cable to source power firstly, then plug headset type-c to headset. Otherwise if plug type-c to headset firstly, headset will power off and switch to wired mode automatically.

6. DETACHABLE MICROPHONE PORT

- when the detachable microphone is not attached, the headset internal microphone works
- if inserting the detachable microphone, headset switches to this external detachable microphone

PROMPT VOICE

- 1) low battery voice prompt will be activated 20 minutes before headset power off. It will be 3 beeps every 5 minutes, so 20 minutes will have 4 times reminder

- 2) One beep: microphone mute
- 3) Two beep: microphone on
- 4) Female voice: power on/off

SPECIFICATIONS

Version: 2.4G + BT + 3.5 mm triple mode
Bluetooth solution: JL7018M
Standard 2.4 GHz ISM band;
sampling rate 48 kHz; 2M bandwidth;
Connection distance: 15 m
RF output power: 10 dBm;
Receiving sensitivity -70 dBm;
Signal to noise ratio 85 dB;
Delay <30ms

Driver: 53 mm
Impedance: 32 Ω ±15%;
Horn sensitivity: 114 dB ±3 dB
Frequency range: 20 Hz - 20 kHz;
Microphone diameter: Φ6.0 x 5.0 mm
Microphone sensitivity: -38 ±2db
Operating voltage: 3.1V ~ 4.2V
Operating temperature: -40°C ~ +80°C

Compatibility: Win 7 / 8 / 10 / P4 / P5

Working current: about 30 mA

Battery capacity: 600 mAh

Charge management IC: 4056

Charge current: 350 ~ 450 mA

Continuous playing time: about 30 h

PACKAGE CONTAINS

- Headset x1
- 2.4 G receiver x1
- Detachable microphone with sponge x1
- USB to Type-C charging cable x1
- 3.5 mm - Type-C audio cable x1
- Manual x1

WARRANTY CARD / JAMSTVENI LIST

ITEM/MODEL:

Naziv/model proizvoda:

RECEIPT NO. / DATE OF PURCHASE:

Broj i datum računa:

SELLING SPOT (COMPANY):

Prodajno mjesto:

THE CUSTOMER:

Kupac:

WARRANTY PERIOD (YEARS):

5

Jamstveni rok (Godina):

SIGNATURE / STAMP:

Potpis i pečat:

All White Shark products are examined and tested after each stage of the production process and have all the required certificates (EMC, CE, ...). The products are subject to the following warranty conditions: - The warranty period for White Shark products is 36 months (on batteries 6 months) and begins on the day of being sold in the store. - The warranty can only be claimed upon presentation of the original purchase invoice and a filed warranty paper with a stamp from the store it was bought at, and if the product has original packaging and all components and equipment - All malfunctioning of the product resulting from factory defects, that occur during the warranty period, and in the normal use of the product in compliance with all instructions will be removed. This warranty covers only defects in material and production. - If the product malfunctions during the warranty period, your White Shark distributor will give you the product (after which is checked by a professional) repaired or replaced. - If the repair at the authorized service center is not completed within 30 days of being received at the service center, we will replace the product with a new one. If the repair during the warranty period lasts longer than 15 days, the warranty period is extended by as many days as the repair lasted. - If the device needs to be repaired within the warranty period, contact the store where you bought the product. If the product has to be sent to an authorized service center or general distributor, please send the product (with all parts and accessories) in the original packaging and with all the necessary documents (invoice, warranty card, etc.). The product can be repaired only in the authorized service center of the importer. The costs of shipping the product to the service center are funded by the customer. Possible damage to the product that can occur during transport is at the expense and risk of the buyer. Sending the product from the service center to the customer is funded by the service technician/the importer. This warranty does NOT cover: - Damage or malfunctions that would occur as a result of incorrect connection, incorrect polarization, incorrect battery placement, etc. - Defects caused by improper handling of products, use of parts or equipment that is not prescribed by our specifications, unauthorized product modification, and defects mechanical damage to the product. - Defects that can occur due to product fall, use of force, natural disasters (flood, fire, thunder, earthquake, ...) due to battery leakage, due to unstable 220V voltage, frequent variations and/or power outages, etc. - Damage caused during transport to the customer. - Products that have been opened or repaired by an unauthorized person. - Parts that are considered consumables such as batteries, etc.

Svi White Shark proizvodi su provjereni i testirani nakon svake faze proizvodnog procesa te imaju sve potrebne certifikate (EMC, CE, ...) te podliježu sljedećim jamstvenim uvjetima: - Jamstveni rok na White Shark proizvode je 36 mjeseci (na baterije 6 m.) i počinje teći danom prodaje u trgovini. - Jamstvo se može ostvariti samo uz prednošenje originalnog računa o kupnji i uredno popunjenoj jamstvenoj listi. - sa žigom trgovine, te ako proizvod ima originalnu ambalažu i sve sastavne dijelove i opremu. - Svi nedostaci i kvarovi koji su posljedica tvorničkih grešaka i koji su nastali u jamstvenom roku i pri normalnoj uporabi proizvoda i pri postavljanju svih naputaka će biti otklonjeni. Ovo jamstvo obuhvaća samo greške nastale u materijalu i izradi. - Ako se proizvod pokvari tijekom jamstvenog roka, Vaš White Shark distributer će Vam proizvod popraviti ili zamijeniti nakon što ga proveri stručna osoba. - Ako popravak u ovlaštenom servisu nije izvršen u roku 30 dana od primitka u servis, proizvod ćemo zamijeniti novim. U slučaju da popravak u jamstvenom roku traje duže od 15 dana, jamstveni rok se produžuje za onoliko dana koliko je popravak trajao. - Ako se ukaže potreba popravka uređaja u jamstvenom roku, kontaktirajte trgovinu u kojoj ste proizvod i kupili. Ako proizvod treba poslati ovlaštenom servisu ili generalnom distributeru, molimo Vas da kompletan proizvod (sa svim dijelovima i opremom) budete zapakiran u originalnu ambalažu te da priložite sve potrebne dokumente (račun i ovjereni jamstveni list). Popravak aparata vrši se isključivo u ovlaštenom servisu uvoznika. Troškove prijevoza proizvoda na servis snosi kupac. Kupac preuzima rizik za moguća oštećenja tijekom prijevoza. Slanje proizvoda od servisa do kupca snosi serviser tj. uvoznik. Ovo jamstvo NI obuhvaća: - Oštećenja ili kvarove koji su nastali kao posljedica nepravilnog priključivanja, krive polarizacije, pogrešnog stavljanja baterija i sl. - Kvarove nastale zbog nepropisnog rukovanja proizvodom, korištenja dijelova ili opreme koja nije propisana našim specifikacijama, neovlaštenog modificiranja proizvoda te kvarove nastale mehaničkim oštećenjem proizvoda - kvarove koji mogu nastati uslijed pada proizvoda, uporabe sile, više sile tj. elementarnih nepogoda (poplava, požar, grom, potres, ...) uslijed curenja baterije, uslijed nestabilnog 220V napona, čestih varijacija i/ili nestanka struje i sl. - Oštećenja nastala pri prijevozu do kupca. - Proizvod koji je otkloven i/ili popravljan od strane neovlaštene osobe. - Dijelove koji se smatraju potrošnicima kao što su baterije i sl.



GORILLA PRO

WIRELESS GAMING HEADSET



UPUTE



1. GUMB ZA NAPAJANJE:

- pritisnite i držite 3 sekunde: uključivanje/isključivanje
- jednostruki klik: pauziranje/nastavak reprodukcije glazbe
- dvostruki klik: prebacivanje na sljedeću pjesmu
- trostruki klik: aktiviranje glasovnog asistenta (samo u BT načinu rada)
- U BT načinu rada: jednostruki klik za prihvatanje poziva, ponovni klik za završetak poziva, držanje 2 sekunde za odbijanje poziva
- Status gašenja: pritisnite i držite gumb za napajanje 10 sekundi za brisanje zapisa uparivanja

2. GUMB ZA ISKLJUČIVANJE/UKLJUČIVANJE MIKROFONA I NAČIN RADA

- uključivanje/isključivanje mikrofona (zadano je uključen mikrofoni)
- dvostruki klik za prebacivanje na prethodnu pjesmu
- trostruki klik za prebacivanje između načina rada za igre i glazbe
- dugo pritiskanje 3 sekunde za prebacivanje između 2.4G i BT načina rada

3. GUMB ZA GLASNOĆU

- okretanje prema gore za pojačavanje, okretanje prema dolje za smanjenje glasnoće

4. INDIKATOR STATUSA

- BT način rada s plavom LED diodom, 2.4G način rada s bijelom LED diodom,
- tijekom punjenja baterije svijetli crvena LED dioda, kada je potpuno napunjeno, plava LED dioda svijetli

5. PRIKLJUČAK ZA PUNJENJE / AUDIO ULAZNI PRIKLJUČAK

- priključite kabel za punjenje, podrška za rad tijekom punjenja

Napomene:

Da bi se podržala funkcija slušalice koje rade tijekom punjenja, korisnici moraju prvo priključiti USB kabel na izvor napajanja, a zatim priključiti tip-C kabel na slušalice. Inače, ako se prvo priključi tip-C na slušalice, slušalice će se automatski isključiti i prebaciti u žični način rada..

6. ODVOJIVI PRIKLJUČAK ZA MIKROFON

- kada odvojivi mikrofoni nije pričvršćen, radi unutarnji mikrofoni slušalice
- umetanjem odvojivog mikrofona slušalice prelaze na ovaj vanjski odvojivi mikrofoni

GLASOVNI PODSJETNIK

- 1. glasovni podsjetnik o niskom naponu baterije aktivirat će se 20 minuta prije isključivanja slušalice. Bit će 3 zvučna signala svake 5 minute, tako da će biti 4 podsjetnika u 20 minuta
- 2. jedan zvučni signal: mikrofoni isključen
- 3. Dva zvučna signala: mikrofoni uključeni
- 4. Ženski glas: uključivanje/isključivanje

KARAKTERISTIKE

Verzija: 2.4G + BT + 3.5 mm 3u1 gaming slušalice
BT čip: JL7018M
Standardni 2.4 GHz ISM pojas;
Frekvencija uzorkovanja 48 kHz; širina pojasa 2M;
Domet: 15 m
Izlazna snaga RF-a: 10 dBm;
Osjetljivost prijema -70 dBm;
Odnos signal/šum 85 dB;
Kašnjenje <30 ms

vučnik: 53 mm
Impedancija: 32 Ω ±15%;
Osjetljivost zvučnika: 114 dB ±3 dB
Frekvencijski raspon: 20 Hz - 20 kHz;
Promjer mikrofona: Φ6.0 x 5.0 mm
Osjetljivost mikrofona: -38 ±2 db
Radni napon: 3.1 V ~ 4.2 V
Radna temperatura: -40°C ~ +80°C

Radna struja: oko 30 mA
Kapacitet baterije: 600 mAh
IC za upravljanje punjenjem: 4056
Struja punjenja: 350 - 450 mA
Neprekidno vrijeme reprodukcije: oko 30 sati

SADRŽAJ PAKIRANJA

- Slušalice x1
- 2.4G prijemnik x1
- Odvajivi mikrofoni sa spužvom x1
- USB na Type-C kabel za punjenje x1
- 3.5 mm - Type-C audio kabel x1
- Upute x1

